



Oscillator JOX254H(V) · (VC)OCXO

- oven controlled crystal oscillator (OCXO or VCOCXO)
- HCMOS output, 25.4 mm x 25.4 mm
- superior frequency stability, best option ± 0.5 ppb
- wide temperature range up to -40 °C ~ $+85$ °C
- frequency control option available (VCOCXO)
- supply voltage options 3.3 V, 5.0 V (option 12.0 V)



RoHS compliant



Pb free



REACH compliant



Conflict mineral free

GENERAL DATA (OVERVIEW OF OPTIONS)

| TYPE | | JOX254H / JOX254HV |
|---|-----------------------|---|
| frequency range | | 10.0 ~ 100.0 MHz (see table 1) |
| frequency tolerance / stability | at +25 °C (*1) | ± 50 ppb / ± 100 ppb max. |
| | temperature (*2) | ± 0.5 ppb ~ ± 50 ppb, examples see table 2 |
| | supply voltage (*3) | ± 0.2 ppb ~ ± 20 ppb max. (at $V_{DC} \pm 5\%$) |
| | load change (*4) | ± 0.2 ppb ~ ± 20 ppb max (at nom load $\pm 5\%$) |
| | aging first year (*5) | ± 50 ppm ~ 300 ppb max. (at +25 °C) |
| | aging per day (*6) | ± 0.5 ppb ~ 5.0 ppb max. (at +25 °C) |
| temperature | operating | up to -40 °C ~ $+85$ °C, see table 2 |
| | operable | up to -40 °C ~ $+85$ °C |
| | storage | -55 °C ~ $+105$ °C |
| supply voltage V_{DC} | | 3.3V ($\pm 5\%$) / 5.0V ($\pm 5\%$) / 12.0V ($\pm 5\%$) |
| steady current consumption | | 250 mA typ. / 400 mA max. (example) |
| warm-up current consumption | | 650 mA typ. / 800 mA max. (example) |
| warm-up time (*7) | | 5 minutes typ. |
| output | low level max. | 0.4 V |
| | high level min. | 2.4 V |
| | duty cycle | 50% $\pm 5\%$ typ. / 50% $\pm 10\%$ max. |
| | rise & fall time max. | 6 ns at nominal load of 15 pF |
| V_C frequ. tuning range JOX254HV | | ± 0.5 ppm min. ~ ± 2.5 ppm min. |
| V_C frequ. tuning voltage JOX254HV | | 1.65 V ± 1.65 V at $V_{DC} = 3.3$ V |
| | | 2.50 V ± 2.50 V at $V_{DC} = 5.0$ V |
| | | 2.50 V ± 2.50 V at $V_{DC} = 12.0$ V |
| input impedance of V_C min. | | 100 k Ω |
| V_C frequ. tuning linearity max. | | 10% |
| phase noise at $f_0 = 10.0$ MHz, $V_{DC} = 5.0$ V | at 10 Hz | -125 dBc/Hz typ. |
| | at 100 Hz | -150 dBc/Hz typ. |
| | at 1 KHz | -155 dBc/Hz typ. |
| | at 10 KHz | -160 dBc/Hz typ. |
| | at 100 KHz | -160 dBc/Hz typ. |

TABLE 1: DEVELOPED FREQUENCIES

| | | | | |
|-------------------------|------|-------|---------|-------|
| all frequencies in MHz: | 10.0 | 12.80 | 16.3840 | 19.20 |
| | 20.0 | 38.40 | 40.0 | 100.0 |

TABLE 2: FREQUENCY STABILITY CODE (EXAMPLES)

| frequency stability temperature code | E ± 50 ppb | G ± 20 ppb | I ± 5.0 ppb | L ± 2.0 ppb | N ± 0.5 ppb |
|--------------------------------------|-------------------|-------------------|--------------------|--------------------|--------------------|
| -10 °C ~ +70 °C | F | ○ | ○ | ○ | ○ |
| -20 °C ~ +70 °C | B | ○ | ○ | ○ | ○ |
| -30 °C ~ +85 °C | M | ○ | ○ | ○ | ○ |
| -40 °C ~ +70 °C | N | ○ | ○ | ○ | ○ |
| -40 °C ~ +85 °C | K | ○ | ○ | ○ | ○ |

○ = ask for availability or other frequency stability options

TABLE 3: VC DEPENDENT FREQUENCY TUNING RANGE CODING METHOD

| V_C frequency tuning range of JOX254 | code | minimal | maximal |
|---|------|---------------|---------------|
| options may not be available at all frequencies, individually ask for other options | 05X0 | ± 0.5 ppm | undefined |
| | 10X0 | ± 1.0 ppm | undefined |
| | 0510 | ± 0.5 ppm | ± 1.0 ppm |
| | 0815 | ± 0.8 ppm | ± 1.5 ppm |
| | 0824 | ± 0.8 ppm | ± 2.4 ppm |
| | 1525 | ± 1.5 ppm | ± 2.5 ppm |
| | 25X0 | ± 2.5 ppm | undefined |

TABLE 4: VC CENTER VOLTAGE AND VC RANGE CODING METHOD

| V_C center voltage and V_C range | code | center and range of V_C | at supply |
|--------------------------------------|------|---------------------------|--------------|
| | 16 | 1.65 V ± 1.65 V | ± 3.3 V |
| | 25 | 2.50 V ± 2.50 V | ± 5.0 V |
| | 25 | 2.50 V ± 2.50 V | ± 12.0 V |

Important Note: This generic datasheet can't show all available options. Therefore, please contact our sales team for specific options not shown in this datasheet.

(*1) ~ (*7): Please refer to the examples for test conditions on page 2


ORDER INFORMATION

| 0 | frequency | type | supply voltage | frequency stability code | operating temp. code | control voltage (for JOX254HV) | tuning range (for JOX254HV) | internal spec. code |
|------------|------------------|-------------------------------------|---------------------------------------|--------------------------|----------------------|--------------------------------|-----------------------------|---------------------|
| Oscillator | 10.0 ~ 100.0 MHz | JOX254H = OCXO JOX254HV = VCOCXO | 3 = 3.3 V 5 = 5.0 V 12 = 12.0 V | E ~ N see table 2 | F ~ K see table 2 | see table 4 | see table 3 | |


Example: **0 10.0-JOX254HV-5-N-K-25-05X0-MCBE-LF** (Suffix LF = RoHS compliant / Pb free)

Oscillator JOX254H(V) · OCXO & VCOCXO · PIN TYPE


DIMENSIONS



top view



side view




bottom view

| | |
|----------------------|-------------------------------|
| OCXO | VCOCXO |
| JOX254 | JOX254V |
| # 1: output | # 1: output |
| # 2: GND | # 2: GND |
| # 3: NC | # 3: V_{Control} |
| # 4: NC | # 4: NC (option ref. voltage) |
| # 5: V_{DC} | # 5: V_{DC} |


pin connection

in mm


PACKING



buffer material



cardboard – max. 20 pcs



dimensions in mm

PACKAGING NOTE

- typically supplied in a carton box
- a full carton box contains 20 pcs.

NOTE

- for best supply noise rejection, connect a capacitor of 100 nF and a second capacitor of 10 μF closely to the supply voltage pins
- a separate voltage supply rail ensures the best phase noise

TEST CONDITIONS (EXAMPLES)

- *1: Measured frequency after 15 minutes of operation, observed with $T_A = +25\text{ }^\circ\text{C} \pm 1\text{ }^\circ\text{C}$, at nominal V_{DC} , the nominal load and nominal center V_C (if applicable) and within 30 days after ex-factory. The measured frequency is referenced to the specified nominal frequency.
- *2: T_A varied in the specified operating temperature range. The frequency variation is normalized to $f_{\text{ref}} = (f_{\text{max}} + f_{\text{min}})/2$, at nominal V_{DC} and nominal center V_C (if applicable), and at nominal output load, temperature variable speed less than 2 $^\circ\text{C}$ per minute.
- *3: Frequency variation if V_{DC} is varied by $\pm 5\%$ of nominal V_{DC} , frequency variation is normalized to frequency observed at nominal V_{DC} , nominal center V_C (if applicable), $T_A = +25\text{ }^\circ\text{C}$ and nominal load.
- *4: Frequency variation if the load is varied by $\pm 5\%$ of nominal load, frequency variation is normalized to frequency observed at nominal V_{DC} , nominal center V_C (if applicable), $T_A = +25\text{ }^\circ\text{C}$ and nominal load.
- *5: Long-term maximum frequency deviation at $T_A = +25\text{ }^\circ\text{C} \pm 1\text{ }^\circ\text{C}$ over the specified time, referred to the ex-factory status at constant T_A , nominal V_{DC} , and nominal V_C (if applicable). The frequency reference is determined at $T_A = +25\text{ }^\circ\text{C}$, at nominal V_{DC} , nominal center V_C (if applicable), nominal load and 30 days of operation. Normally, the largest frequency deviation occurs within the 1st year.
- *6: Maximum frequency deviation within 24 hours in a steady state. The initial status acquired at $T_A = +25\text{ }^\circ\text{C}$, at nominal V_{DC} , nominal center V_C (if applicable), nominal load and after 30 days of continuous operation.
- *7: Time until the maximum frequency deviation is less than a specified value, referred to the final frequency. This final frequency is acquired after 1h of continuous operation at $T_A = +25\text{ }^\circ\text{C}$, at nominal V_{DC} , nominal center V_C (if applicable) and nominal load.